

RADIAS System Firmware Update

Update Procedure for Windows users

⚠ This updater is compatible with Windows XP, do not try to run it with Windows 98/Me.

⚠ The "KORG USB-MIDI Driver" needs to be installed before the update.

See the "CD-ROM/Manual" included with the RADIAS.

⚠ In addition, The "KORG USB-MIDI Driver" needs to be Version 1.08 or later.

If the driver installed on your computer is older than Version 1.08, install the latest version of the driver before starting the update.

1. Set the Power Switch of the RADIAS to the [STANDBY] position, and connect to a computer using a USB cable.
2. Unzip the RADIAS_Updater_xxxx.zip file (xxxx is a version number).

⚠ Unzip all the files in the zip file before proceeding to [Step 2]. The updater will not be able to find all the necessary files if they were not unzipped.

3. Turn on the Power Switch of the RADIAS while holding the [MASTER FX ON], [Cursor(Up/Left)], and [Cursor(Down/Right)] keys. This will put it in "Update Mode".

The following messages will appear in the display. (The version number of "SYS", "USR", and "PCM" may different from these numbers):

RADIAS Verup Mode...


By USB-MIDI

SYS : Ver 1.02

USR : Ver 1.01


PCM : Ver 1.01

4. Execute the kmupdate.exe. The following window will appear: (This is the image of the updater window when the RADIAS version is 1.02, and the latest version is 1.07)




5. Push the [Update] button in the window to start the process.

 If the following message is shown, the system firmware is already up to date, and no change is needed. In this case simply quit the KORG System Updater.




- ▲ If an “Error message” is shown, confirm that the “RADIAS” is connected to the computer properly, the “KORG USB-MIDI Driver” has already been installed and is showing RADIAS, and not “USB audio device”, and the driver is Version 1.08 or later.
 - ▲ The updater can’t recognize the RADIAS if [Step 3] and [Step 4] are not done in the right order.
6. During the updating process, the following window will appear. The whole process will take several minutes to complete.



▲ **Do not turn off the RADIAS during the update process.**

- The following message will be shown when the update has successfully completed.
This will conclude the entire update procedure.



- Quite the KORG System Updater, and reboot the RADIAS.
- You can confirm the current system version by turning on the RADIAS in Update Mode, as described in [Step 3]. If you choose to do this, you will need to reboot the RADIAS after verifying that the current system is successfully updated.